


Tools Required:

- 2mm hex key
- Flat head screw driver medium
- Phillips head screw driver medium

CSA certified to U.S. and Canadian standards.
Suitable for wet locations.



Dimensions

- A: 6-7/8 "
- B: 3-7/8 "
- C: 2-3/8 "



Protection Class: IP64
Weight: 1.54 lbs

Notice to Installer for 2261LED:

1. For wall applications only.
2. Mounts directly to wall over standard octagonal 4" wiring box (by others).
3. In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.

2261LED - installation:

1. Remove luminaire mounting plate by loosening (2) 3mm set screws on rear canopy of fixture.
2. Feed luminaire wires through back of luminaire mounting plate.
3. Make supply wiring and luminaire wiring connections in small opening wiring box:
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
- Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
5. Attach luminaire base to wall by using (2) 1 1/2" 8-32 mounting screws (by others).
6. Place a small bead of silicone around the back side of the luminaire base that will come in contact with the finished wall (exterior applications only).
7. Mount luminaire to luminaire base, making sure orientation label is aimed correctly. Tighten 3mm set screws to secure.

Relamping/Maintenance

No relamping required.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
Face Plate	FP2261
Driver (120-277V)	75929
LED (3000K)	LED-0141/830
LED (4000K)	LED-0141/840

Lamp: 6.6 W LED Module

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.