

TRACK QUICK CONNECT TRANSFORMER ADAPTOR

MODEL EN-XQ50AR



Ordering Matrix

Model	Series	Finish						
[]	[]	[]						
EN	HQ50AR JQ50AR LQ50AR	<table border="1"> <tr> <td style="text-align: center;">BK</td> <td style="text-align: center;">BN</td> <td style="text-align: center;">WT</td> </tr> <tr> <td colspan="3" style="text-align: center;"><i>DB only available for HQ50AR</i></td> </tr> </table>	BK	BN	WT	<i>DB only available for HQ50AR</i>		
BK	BN	WT						
<i>DB only available for HQ50AR</i>								

Ordering Example (*model number – series – finish*): EN-HQ50AR-BK

Product Details

Description: The EN-__50AR is a track adaptor with an integral 50 watt electronic transformer. The quick connect transformer adaptor allows low voltage quick connect elements, either track heads or pendants, to be used with the WAC's H, L, J & J2 track systems.

Materials: Polycarbonate case with metal fittings for attaching to rail. Transformer is a high frequency 12V electronic transformer.

Fixtures: Compatible fixtures include all the elements in the WAC Lighting quick connect series of pendants and track heads. Lamp loading wattage when using the EN-__50AR is 1-50 watts.

Systems: HQ50AR = H system track
JQ50AR = J & J2 system track
LQ50AR = L system track

Input: 120V (50/60Hz)
Output: 12V

Finish: BK = Black BN = Brushed Nickel WT = White
DB = Dark Bronze

Dimming: Dimmable with electronic low voltage dimmers.

Listing: UL & CUL Listed.

Specification Features

- The EN-__50AR threaded nipple is compatible all with the following quick connect pendant socket sets; QP-501, QP-502, QP-601 QP-701, QP-902, QPLED series
- Electronic transformer has advanced auto-reset, soft start and short circuit protection features. The soft start delayed lamp start feature extends lamp life by delaying the abrupt inrush current to the lamp.
- 5 year WAC Lighting product warranty.