

MonoRail Surface Transformer-100W EI LED 



DESCRIPTION

This single-feed surface transformer converts standard 120 line-voltage to 12 volts to provide the necessary voltage for powering a MonoRail low-voltage lighting system. It can power lamps totaling up to 100 watts. The transformer is concealed inside a decorative housing with a fast acting secondary circuit breaker that will safely turn the system off should a short occur. Once the short has been removed the unit can be reset by simply flipping the wall switch off and back on.

INSTALLATION


This product can mount to either a 4" square electrical box with round plaster ring or an octagon electrical box (not included). Rail is installed through the power feed on the canopy to bring power to the run.

DIMMING

Dimmable with a 600 watt low-voltage electronic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics).

OTHER INFORMATION

Black and white finish have satin nickel feeds. The shortest rigid standoff that can be used with this surface transformer is the 3" rigid standoff (sold separately). If dropping the rail more than 3" below the ceiling, order the desired rigid standoff length and one compatible power extender (sold separately).



ORDERING INFORMATION

700MOSRT100E FINISH

- Z- ANTIQUE BRONZE
LED
- B- BLACK
LED
- C- CHROME
LED
- S- SATIN NICKEL
LED
- W- WHITE
LED



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700MOSRT100E _____
FIXTURE TYPE: _____
JOB NAME: _____
NOTES: _____

