


# Surface Transformer

SINGLE-FEED, 24 VOLTS 300 WATTS



Shown approx. 20% actual size.



kl\_srt3024d\_spec.pdf

August 2005 Specifications subject to change without notice.

## DESCRIPTION

This single-feed surface transformer converts standard 120 volt line-voltage to 24 volts to provide the necessary voltage for powering a Kable Lite system. It can power lamps totaling up to 300 watts. The transformer is concealed inside a decorative housing with a fast-acting secondary circuit breaker that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.

## INSTALLATION

This product can mount to either a standard 4" square electrical box with round plaster ring or an octagon electrical box (not included).

## DIMMING

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics). This surface transformer includes a preinstalled debuzzing dimming coil to reduce audible noise when using a low-voltage dimmer.

## FINISH

Chrome, satin nickel, black, white. Black and white finish have chrome feeds.

## COMPATIBLE RIGID STANDOFFS

The shortest rigid standoff that can be used with this surface transformer is the 5" rigid post standoff (sold separately).

## OPTIONS

This surface transformer may be plugged in with the addition of a Plug Option, a 16 foot cord with inline switch two feet from the plug (sold separately).

## REQUIRED USAGE

24 volt transformers require the use of 24 volt lamps.

## WEIGHT

12.15 lb./5.51 kg. ±

## ORDERING INFORMATION

700SRT3024D	FINISH
	C CHROME
	S SATIN NICKEL
	B BLACK
	W WHITE



7400 Linder Avenue T 847.410.4400  
 Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com



700SRT3024D \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_