



## 87843MB

### CounterMax MX-X120c 30" 4-Light 120V Xenon

With a sleek profile, linkability and direct wiring, CounterMax MX-X120c Series installs easily under the cabinet and emits a warm light. The hinged top gives easy access to the long-lasting Xenon bulbs and wiring. Cabinets stay cool and safe due to the unique airflow design that limits heat transfer.

#### Finish

Metallic Bronze

#### Glass/Shade

#### Product Category

Under Cabinet

#### Lamping

Number of Bulbs	4
Light Type	Xenon
Bulb Type	G8 T4
Max Wattage	20
Rated Life	3500
Rated Lumens	900
Color Temp	2900
Bulb(s) Included	Yes
Light Up/Down	N/A
Beam Spread	
CRI	

#### Measurements

Width	5.0"
Height	1.3"
Length	30.0"
Extension	0"
Back Plate Width	0.0"
Back Plate Height	0.0"
HCO	0"
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	3.3 lbs

#### Shipping

Carton Weight	3.3 lbs
Carton Width	
Carton Height	
Carton Length	
Carton Cubic Feet	0
Master Pack	6
Master Pack Weight	24.3 lbs
Master Pack Width	12.6"
Master Pack Height	10.6"
Master Pack Length	34.3"
Master Cubic Feet	0
UPS Shippable	Yes

#### Certification

UL/ETL/CSA	
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No

#### Other

UPC Code

#### Equivalents

Incandescent  
Fluorescent

Maxim Lighting International, ET2 Contemporary Lighting and all designs, logos and images © 2010 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Products are subject to revision in design and/or construction to conform to changes in UL and/or CSA standards, or that which may be required by law or availability of material.

Maxim Lighting International products are UL and CSA approved.

Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.