

Lighting Your Life Since 1970

Product Specifications - 87522WT				
Job Name:	Job Type:			
Quantity:	Comments			



ADA

Dark Sky

87522WT

Wrap Around EE 4-Light Flush Mount Milli Amp = 420mA per ballast.

N/A

Steel

<i>Finish</i> White		Glass/Shade White		Product Category Flush Mount	
Lamping Number of Bulbs	4	Measurements Width	13.0"	Shipping Carton Weight	8.8 lbs
Light Type	Fluorescent	Height	2.5"	Carton Width	14"
Bulb Type	Med Bi Pin T8	Length	48.0"	Carton Height	4"
Max Bulb Wattage	32	Extension	N/A	Carton Length	50"
Max Fixture Wattage	128	Back Plate Width	N/A	Carton Cubic Feet	1.52
Rated Life	±20,000 Hours	Back Plate Height	N/A	Master Pack	1
Rated Lumens	±11,200	нсо	N/A	Master Pack Weight	N/A
Color Temp	±3,000 K	Min Overall Height	N/A	Master Pack Width	N/A
Bulb(s)	Not Included	Max Overall Height	N/A	Master Pack Height	N/A
Light Up/Down	N/A	Hanging Weight	8.8 lbs	Master Pack Length	N/A
Beam Spread	N/A	Height Adjustable	N/A	Master Cubic Feet	N/A
CRI	N/A	Slope	N/A	UPS Shippable	
Photo Cell Included	N/A	Chain Length	N/A		
Ballast/Driver/Transformer	Yes	Wire Length	N/A		
Dimmable	No	Canopy Width	N/A		
		Canopy Height	N/A		
		Canopy Length	N/A		
		cunopy Longui			
Certification		Other		Equivalents	
Safety Rating	Drv	UPC Code	783209022416	Incandescent Watts	1018
Energy Star	No	Shades Included	N/A	Fluorescent Watts	N/A
				Fluorescent Walls	IN/A
CA Title 24	Yes	Crystals Included	N/A		
CA Title 20	No	Diffuser Included	N/A		

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

No

N/A

Conversion Kit

Material

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.