


Replacement Parts:

LED Module	LED-0124/830
LED Driver	75951
Glass Lens	140898



Dimensions

- A:** 4-1/8"
- B:** 15-3/8"
- C:** 4-3/8"



CSA certified to U.S. and Canadian standards. Suitable for wet locations.

Protection Class: IP65

Weight: 2.4 lbs.

Luminaire 7903LED:

Housing: Reinforced polyimide synthetic housing for maximum corrosion resistance. Reflector made of pure anodized aluminum. Clear safety glass.

Electrical: 4.5W LED luminaire, 6 total system watts, -30°C start temperature. Integral 12V AC driver provided. Standard LED color temperature is 3000K with an 83 CRI.

IMPORTANT: For use with magnetic landscape transformers **ONLY**.

Warranty: 3 year manufacturer warranty.

Notice to Installer for 7903LED:

WARNING: LEDs are high quality electrical components. Please avoid opening upper electrical compartment and do NOT touch LED module.

1. Compatible for use with 12-24V AC input voltage.
2. Voltage must NOT drop below 10V.
3. Turn main power OFF before start of installation.
4. Horizontal rotation: 355°
5. Vertical rotation: +70°/-30°
6. No tools necessary for rotation adjustment.

7903LED installation:

1. Establish planned fixture location and provide supply wiring.
2. Make wiring connections. For maximum wire run lengths, see table below.
3. Push luminaire with earth spike vertically into the soil until stability is achieved.
4. If necessary compact soil around the earth spike.
5. Adjust position of the floodlight and tighten thumbscrew.

Lamp: Integral 4.5W LED Module
(No replacement necessary)

Max. Run Length (ft) Per Wire Size: 2 Volt drop					
Connected LED Watts	Wire Size (AWG)				
	18	16	14	12	10
40	46	73	116	185	294
30	61	97	155	246	392
20	92	146	232	369	588
15	122	195	309	492	784
10	183	292	464	738	1176
5	366	585	928	1477	2353

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.