



**IMPORTANT
TURN OFF THE POWER AT THE MAIN FUSE
OR CIRCUIT BREAKER BOX
BEFORE STARTING INSTALLATION**

Carefully unpack and identify all parts before assembly. Bulbs are not included.

- This fixture can be mounted onto ceiling either as chain hung or flush mount:
CHAIN HUNG INSTALLATION- Fig. 1:
 A. Thread fixture wires through threaded pipe, cover, and upper leaf. Then install threaded pipe by screwing into top of fixture. Slip cover and upper leaf through protruding threaded pipe. Lock all together by fastening with fixture loop.
 B. At this point, determine the desired length of chain to hang. Remove any unwanted links with chain pliers.
 C. This fixture is supplied with 2 adjustable chain links. These links are opened and closed by twisting cylinder on chain link. One adjustable chain link should be installed onto canopy loop. And another adjustable chain link installed onto the fixture loop. The standard chain should be installed in between these 2 threaded chain links.
 D. Take ground wire and weave through above chain links, then thread through center hole in canopy loop. Repeat with fixture wire (wire with plastic insulation).
FLUSH INSTALLATION- Fig. 2:
 A. Remove and discard canopy loop and threaded pipe from canopy.
 B. Install threaded pipe by screwing into top of fixture.
 C. Thread fixture wires through cover, canopy leaf, canopy, lock washer, and hex nut. Lock all together on top of fixture by tightening hex nut onto protruding threaded pipe.
- Cut excess wires leaving only 6" (15 cm) length of wires above canopy. Split fixture wire into two strands. Then strip off 3/4" (19mm) of outer plastic insulation.
- Follow enclosed supplement installation instructions for electrical and fixture installation onto house outlet box. If you do not have an outlet box at desired location to attach the fixture than hire a qualified electrician to create one.
- Slip candle tube over sockets.
- Install bulbs (not included). See relamping label located near socket area for type and maximum allowed wattage.
- Hang all crystal glass parts as shown on drawing. NOTE: To replace broken crystals extras are included in hardware bag. Replace by gently bending open pin, remove broken crystal, hook new one, then close back pin. Avoid bending pin into sharp angle.