



LOW VOLTAGE ELECTRONIC TRANSFORMER

MODEL EN-1260-P-AR



Ordering Matrix

Model	Finish	Accessories
EN-1260-P-AR	BK WT	See table below

Ordering Example (model – finish) : EN-1260-P-AR-BK

Product Details

Description: Low Voltage plug-in Class II electronic transformer designed to be used as portable or plug-and-play style transformer. Contains an on/off toggle switch at the base and a 6' detachable cord with INVISILED® connections. Do not used with LED button lights.

Catalog Number: EN = Advanced electronic circuitry
1260 = 12 volt , 60 watt
P = Portable Plug-In
AR = Auto-Reset

Input: 120V (50/60Hz)
Output: 12V

Min Load: 20W
Max Load: 60W
Max Input Amp: 0.53A (@ 120V)

Transformer Frequency: 20 khz.
True RMS meter is required to read the high frequency output.

Listing: U.L. listed, File Number E204239.

Accessories: MTB-01 – Multiple Terminal Block

Specification Features

- U.L. 2108 listed Class II electronic low voltage transformer.
- Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.
- Class II transformers are inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits
- EN-1260-P-AR is dimmable, consult WAC for dimmer options.
- 5 year WAC Lighting product warranty.