



TRANS-SFM150-SC-LED

Watt & Type: 12 volt/150 watt Magnetic Toroidal

Input: 1x120VAC/1.25A

Output: 1x150W

Compatible Dimmer: Magnetic Low Voltage Dimmer, 600W
Lutron is recommended

Fusion Transformers

All monorail lighting systems require a transformer to convert standard 120 voltage to a safe-to-touch 12 volts. Fusion Monorail can be powered with surface mounted transformers or with remote transformers.

Surface Mounted Transformers

All Fusion surface mounted transformers are encased in a satin nickel metal housing and mount to any standard ceiling electrical box.

Typically, you use a surface transformer when an accessible location above the ceiling or in a utility closet is unavailable for installing a remote transformer.

150, 300 and 600 watt surface mounted transformers are available to power your system. Single feed (150 and 300 watt) and double feed (600 watt) 10 AWG flexible coaxial feeder (patent pending) cleanly and attractively sends power to your system. 36" length is standard for our coaxial feeder. It is easily shortened in the field. Consult factory for longer lengths.