## WARNING! SHUT POWER OFF AT FUSE **OR CIRCUIT** BREAKER .

- ASSEMBLING THE FIXTURE (Fig.2).
- Attach the loop (A) to center of the part (B) by turning it clockwise 1 until tight.
- Feed fixture wires through center tube (B). Connecting center part 2 (B) to the frame (H) and turn clockwise until firmly tightened.
- 3 Hook the end of arms (E) to the hook on the part (B) and the frame (H)
- Thread the nipple (J) into coupling located on bottom of the frame 4. (H) and secure it with the hex nut (I). Raise the finial base (K) and the decorative arm (L) over the nipple (J) and thread the finial (M) onto the nipple (J).
- Place the socket sleeve (F) over the socket (G) of the fixture body 5. (H). Install the light bulbs and clip the cloth shades (D) on to the bulbs, then screw the finial (C) onto shades (D).

6. Install the light bulbs in accordance with the fixture specifications NOTE: DO NOT EXCEED THE SPECIFIED WATTAGE!

## HANGING THE FIXTURE (Fig.1)

- Shut off the power at the circuit breaker and remove old fixture 1. from ceiling, including the old crossbar.
- 2. Carefully unpack new fixture and lay all the parts on a clear surface.
- 3. Thread nipple (C) into loop (F) until snug.
- Thread other end of nipple (C) with loop attached into crossbar (D) 4. until snug.
- Place lock washer (B) over end of nipple protruding through 5 crossbar and thread hex nut (A) onto nipple until tight.
- Take this crossbar assembly and mount to ceiling junction box with 6 junction box screws (E). Tighten screws securely with screwdriver.
- 7. Using proper chain pliers to open one end link of the chain provided and connect to the fixture loop (I). Close the link.
- 8 By measuring, determine correct number of links needed for proper hanging height. Using proper chain pliers disconnect and discard remaining chain.
- Lace the fixture wires through the chain.
- 10. Slip loop collar (H) over the chain, then do the same with the canopy (G).
- 11. Open the other end link of the chain and hang the fixture on the loop at the ceiling. Close the link.
- 12. Feed the fixture wires through the loop (F) and nipple (C) and pull until taut.
- 13. Slide canopy (G) up flush to ceiling, secure using loop (H).
- CONNECTING THE WIRES (Fig.3)
- Take the black wire from the ceiling junction box and the smooth 1. wire leg from the fixture and twist bare ends together. Twist wire connector onto end of wire until snug.
- 2. Repeat same process with white junction box wire and ribbed wire leg of fixture wire. NOTE: Twist wires together in the same direction you twist the wire connector onto wires.
- If your junction box has a grounding wire (green or bare copper), 3. attach this wire and the bare copper wire from the fixture together as step 1.If junction box has no ground wire, attach the bare copper fixture wire to the green ground screw on the crossbar.
- Tuck these wire connections neatly into the ceiling outlet box and 4 then raise the canopy (G) all the way to the ceiling. Raise the loop (H) and thread onto ceiling loop protruding through canopy

Your installation is now complete. Return power to the junction box and test the fixture.







