



Catalog Number
Notes
Type

## FEATURES & SPECIFICATIONS

### INTENDED USE

Provides accent illumination that visually expands the space and creates a relaxing atmosphere in residential and commercial applications such as hospitality, educational, health care and circulation areas. Ideal for use in hallways, stairways, dining areas, foyers, offices and meeting rooms.

### CONSTRUCTION

A classic look, this transitionally styled sconce is offered in a hand-dipped, tea-stained glass shade mounted on an antique bronze finished socket housing and matching decorative support arm/canopy or acid-etched, frosted glass shade mounted on a brushed-nickel finished socket housing and matching decorative support, arm/canopy. The shade provides a widespread uniform illumination.

Includes (1) 13W integrated GU24 spiral 2700K fluorescent lamps/ballasts (see note below) for energy efficiency, superior color rendering and long life.

Standard with electronic ballast (120 volt, 60Hz) ensures no flickering and quiet operation without interfering with other home electronics.

Included lamps are for use with non-dimmable switches only. If fixture is supplied with integrated lamps/ballasts and tall sockets (see note below), dimmable lamps (CF15INLB27 GU24 DIM) can be used (sold separately).

All mounting hardware included.

### LISTINGS

CUL listed to US and Canadian safety standards and suitable for damp locations. ENERGY STAR® qualified.

### WARRANTY

Guaranteed for two years against mechanical defects (excludes lamps).

Indoor Decorative


# Ferros Sconce

Compact Fluorescent



### Dimensions

All dimensions are inches (centimeters)



Backplate Dimensions:

Width: 4-1/2" (11.4)

Height: 6-1/2" (16.5)

**NOTE:** Older fixtures may have shipped with pin-based lamps and SU13 ballasts. To identify the correct replacement lamps, look at the sockets.



#### Tall Sockets

Uses GU24 integrated lamps/ballasts (CF13INLB27 GU24)



#### Short Sockets

Uses pin-based lamps (CF13S27) AND SU13 ballasts (BLST SU 13W)

### ORDERING INFORMATION

For shortest lead times, configure products using **bolded options**.

**Example:** 11531 BZA

Series	Finish	Ballast/Voltage	Options
<b>11531</b> (1) 13W lamps included	<b>BZA</b> Antique bronze with tea-stained glass <b>BN</b> Brushed nickel with opal glass	(blank) 120 volt residential electronic ballast (standard)	(consult factory)

**Accessories:** Order as separate catalog number.

<b>CF13INLB27 GU24</b>	13W integrated GU24 spiral 2700K fluorescent lamp/ballast
<b>CF13S27</b>	13W compact full spiral 4-pin 2700K fluorescent lamp
<b>BLST SU13W</b>	13W GU 24-pin-base socket G24q1 4-pin
<b>DFERO TST</b>	Tea-stained glass shade
<b>DFERO WH</b>	Opal glass shade

## Ferros Sconce - Decorative Fluorescent

---

### PHOTOMETRICS

Full photometric data report available within 2 weeks from request. Consult factory.