
Veryon Head







DESCRIPTION

16 watt, 800+ lumen directional LED head made of machined aluminum housing and extruded aluminum he at sink. The LED is easily field replaceable and upgradable due to the solderless connector. The heat sink remains with the fixture minimizing any waste at the end of the lamp module 's life. The two-tone finish adds a modern industrial aesthetic. The head rotates 360° and pivots 90° to direct the beam. Integrated lens holder accommodates one lens or louver (sold separately). Dimmable to 10% with low-voltage electronic or magnetic dimmer.

Available for FreeJack, MonoRail, and Two-Circuit MonoRail. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system.

DIMMING

Dimmable to 10% with low-voltage electronic or magnetic dimmer (not included).

ACCESSORIES & OPTICAL CONTROLS

Colored Lens, Dichroic Lens, Diffuser Lens, Eggcrate Louver, Linear Spread Lens, Soft Focus Lens, UV Filter

ORDERING INFORMATION

700	SYS	TEM VRN	SHAPE OR SIZE	LENGTH FINISH	
	FJ	FREEJACK (MONO	831680 CRI 3000K LED	03 3"	S SATIN
		POINT)	16°	06 6"	NICKEL
	MO	MONORAIL	832880 CRI 3000K LED	12 12"	
	MO2	TWO-CIRCUIT	28°	18 18"	
		MONORAIL	834580 CRI 3000K LED		
			45°		

Note: When installing on MO2 only magnetic transformers may be used.



www.techlighting.com

700 VRN					
FIXTURE TYPE:					
JOB NAME:					
NOTES:					

