

FreeJack Linear Canopy 3-port



DESCRIPTION

Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformers inside a 28" by 4" housing. Three FreeJack ports; for ceiling only.

INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). For ceiling only. Transformers (included) fit in canopy.

DIMMING

120V IN/12V OUT dimmable with a standard incandescent dimmer (not included). 120V LED dimmable with a low-voltage electronic dimmer.


OTHER INFORMATION

"For use with any three 12 volt halogen or LED FreeJack pendants or heads (sold separately)."

WEIGHT

7.3lb / 3.31kg

ORDERING INFORMATION



700FJL3 FINISH	VOLTAGE
Z ANTIQUE BRONZE	120V IN/12V OUT
B BLACK	
C CHROME	-277 277V IN/12V OUT
S SATIN NICKEL	
W WHITE	



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
 Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700FJL3 _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____

