

Wall MonoRail Remote Kit 300w



DESCRIPTION

Includes 8' long hand-bendable MonoRail, one set of decorative end caps, three Wall MonoRail standoffs, an end power feed, and a 12 volt 300 watt plug-in remote magnetic transformer. Add up to six 50 watt elements or up to eight 35 or 37 watt elements.

INSTALLATION

Magnetic transformer installs in an accessible location behind the ceiling or wall. Canopy mounts to a standard 4" junction box with round plaster ring (provided by electrician) and includes 24" softwire leads.

DIMMING

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics.)

ORDERING INFORMATION

700WMKTA300 FINISH

- Z ANTIQUE BRONZE
- C CHROME
- S SATIN NICKEL



www.techlighting.com

| |
|---------------------|
| 700WMKTA300 _____ |
| FIXTURE TYPE: _____ |
| JOB NAME: _____ |
| NOTES: _____ |
| _____ |
| _____ |



©2012 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.