

Product Specifications - 82688MRSN				
Job Name:	Job Type:			
Quantity:	Comments			
,				



82688MRSN Malibu ES 3-Light Bath Vanity



Finish Satin Nickel		Glass/Shade Marble		Product Category Bath Vanity	
Lamping	2	Measurements	40.5"	Shipping Contain Mainta	N1/A
Number of Bulbs	3	Width	19.5"		N/A
Light Type	Fluorescent		6.0"	Carton Width	22"
Bulb Type	GU24		0.0"	Carton Height	10"
Max Bulb Wattage	13	Extension	8"	Carton Length	8"
Max Fixture Wattage	39	Back Plate Width	N/A	Carton Cubic Feet	1.05
Rated Life	±10,000 Hours	Back Plate Height	N/A	Master Pack	1
Rated Lumens	±2,700	нсо	N/A	Master Pack Weight	N/A
Color Temp	±2,700 K	Min Overall Height	N/A	Master Pack Width	N/A
Bulb(s) Included	Yes	Max Overall Height	N/A	Master Pack Height	N/A
Light Up/Down	N/A	Hanging Weight	N/A	Master Pack Length	N/A
Beam Spread	N/A	Height Adjustable	N/A	Master Cubic Feet	N/A
CRI	81-82	Slope	N/A	UPS Shippable	Yes
Photo Cell Included	N/A				
Ballast	N/A				

Certification		Other		Equivalents	
UL/ETL/CSA	Damp	UPC Code	783209076402	Incandescent Watts	N/A
Energy Star	Yes	Shades Included	N/A	Fluorescent Watts	N/A
CA Title 24	Yes	Crystals Included	N/A		
CA Title 20	No	Diffuser Included	N/A		
ADA	Yes	Conversion Kit	N/A		
		Material	N/A		

Maxim Lighting International and all designs, logos and images © 2010 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Products are subject to revision in design and/or construction to conform to changes in UL and/or CSA and/or ETL standards, or that which may be required by law or availability of material.

Maxim Lighting International products are UL, ETL or CSA approved.

Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.