

## SPECIFICATIONS:

### DESCRIPTION

Low voltage mini pendant with handcrafted glass.  
Includes Quick-Connect jack.

### LAMPING

50W Low pressure halogen GY6.35 12V Bi-Pin lamp, included.  
Suitable for use in an open fixture. Optional lamp shield also available.

### DIFFUSER

Shade shall be handcrafted glass of various decors.  
Diameter of 4.5" and height of 3.5"

### CORD

Standard cord is 10' field-adjustable coaxial type with teflon jacket and decorative sleeve at the socketholder. Jacket tint coordinates with metal finish. Cords also available in 36", 48" or 15' lengths.

### QUICK-CONNECT JACK

Quick-Connect jack is compatible with Besa Rail Adapter, or Quick-Connect canopies (order separately).

### METAL FINISH

Glass retainer hardware, sleeve and Quick-Connect jack are finished in either Bronze or Satin Nickel.

### ELEMENT OPTIONS


Refer to next page. Available as Quick-Connect element only, or with Rail Adapter for use with Besa Monorail, or with 1 light Quick-Connect canopy.

### LABELS

ETL or UL Listed. Suitable for Dry Locations (interior use only).



### Glass Dimensions:



5440DW  
Black Dicro Wavy



5440SW  
Silver Dicro Wavy



**For ordering information, see next page**

All dimensions provided are nominal.  
Allowance must be made for dimensional tolerance in handcrafted glasses.


REV 7/10

## ORDERING:

| Quick-Connect Options        | Decor                           | Metal Finish           |
|------------------------------|---------------------------------|------------------------|
| <b>XP</b> Jack Only          | <b>5440DW</b> Black Dicro Wavy  | <b>BR</b> Bronze       |
| <b>RXP</b> Rail-Ready        | <b>5440SW</b> Silver Dicro Wavy | <b>SN</b> Satin Nickel |
| <b>1XP</b> 1 Lt. Flat Canopy | <b>5440VB</b> Black Dicro Vine  |                        |


## PENDANT OPTIONS:

### XP Pendant Element Only



- Pendant Shade and Cord/Socket Set
- 10' Field-adjustable braided coaxial-type cord with a teflon jacket (clear or bronze tint coordinates with metal finish)
- Quick-Connect Jack provided
- Compatible with Besa Canopies and Rail Adapter
- Bronze or Satin Nickel metal finishes


### RXP Pendant + Rail Adapter



#### READY FOR RAIL

- Pendant Shade and Cord/Socket Set, plus Rail Adapter
- 10' Field-adjustable braided coaxial-type cord with a teflon jacket (clear or bronze tint coordinates with metal finish)
- Quick-Connect Jack provided
- Compatible with Besa Monorail System
- Bronze or Satin Nickel metal finishes


### 1XP Pendant + Monopoint Flat Canopy



- Pendant Shade and Cord/Socket Set, plus Flat Canopy
- 1x electronic 60W dimmable transformer, fits partially in junction box
- 10' Field-adjustable braided coaxial-type cord with a teflon jacket (clear or bronze tint coordinates with metal finish)
- Quick-Connect Jack provided
- Integral Quick-Connect adapter
- Bronze or Satin Nickel metal finishes

## Also Available: Fixed-Connect Pendant

### 1XC 1 Light Pendant



#### NO CORD CUTTING REQUIRED

- Suitable for use on sloped ceilings
- 1x electronic 60W dimmable 120V transformer
- Installs to standard 4" octagonal junction box
- Bronze or Satin Nickel metal finishes
- **OPTIONAL:** 277V transformer
- For commercial applications, contact factory

#### 3Ft. CORD LENGTH:

For 36" cord, add an "3" to the end of the item number, i.e. 1XP-174352-SN3.

#### 4Ft. CORD LENGTH:

For 48" cord, add an "4" to the end of the item number, i.e. 1XP-174352-SN4.

#### 15Ft. CORD LENGTH:

For longer 15' cord, add an "L" to the end of the item number, i.e. 1XP-174352-SNL.

## Project Information:

## MORE MOUNTING OPTIONS:

- Besa quick-connect canopies, order separately

3Lt Linear: T23BQ

3Lt Round: T23XQ

3Lt Lrg. Rnd: T23XL

6Lt Round: T26XQ

1Lt Dome: T21MQ

3Lt Bar: T23VQ

4Lt Bar: T24VQ

- Besa Monorail system, order separately