


615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.waclighting.com

CATALOG NUMBER	<u>TYPE</u>
PROJECT	

SOLORAIL™ - SURFACE MOUNT TRANSFORMER

MODEL LM-EN12-300M





Ordering Matrix				_
Model	Part Number		Finish	
LM-EN12	300M	DB	СН	BN

Ordering Example (model number - part number - finish): LM-EN12-300M-CH

Product Details

Description: Surface mount magnetic low voltage transformer for the WAC

Solorail™ system. The canopy style enclosure includes the

transformer and the track power feed adaptor.

Catalog LM = Low voltage Solorail™

Number: EN12 = 12 volt, enclosed canopy transformer

300M = 300 watt magnetic

Input: 120V (50/60Hz)

Output: 12V

Max Load: 300W

Max Input Amp: 2.5A (@ 120V)

Mounting: Installs to a standard junction box. Total weight = 11 lbs.

The standard LM-EN12-300M configuration matches the height

of the 5 3/4" standoffs (LM-X5).

Finish: Available in Dark Bronze (DB), Chrome (CH), and Brushed

Nickel (BN).

Listing: UL & CUL Listed.

Specification Features

- Dims with magnetic low voltage dimmers.
- Output circuit breaker located on the upper lip of the canopy enclosure is a magnetic push to reset type.
- Contains integral de-buzzing coil.
- The surface mount canopy transformer is an ideal choice when the installation is on an existing ceiling.
- 5 year WAC Lighting product warranty.




615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.waclighting.com

CATALOG NUMBER	<u>TYPE</u>
PROJECT	

SOLORAIL™ - SURFACE MOUNT TRANSFORMER

MODEL LM-EN24-300M





Ordering Matrix				
Model	Part Number		Finish	
LM-EN24	300M	DB	СН	BN

Ordering Example (model number - part number - finish): LM-EN24-300M-DB

D,	\mathbf{o}	HICT	$\mathbf{n}_{\mathbf{a}}$	taile
F		uct		talls

Description: Surface mount magnetic low voltage transformer for the WAC

Solorail™ system. The canopy style enclosure includes the

transformer and the track power feed adaptor.

Catalog LM = Low voltage Solorail™

Number: EN24 = 24 volt, enclosed canopy transformer

300M = 300 watt magnetic

Input: 120V (50/60Hz)

Output: 24V

Max Load: 300W

Max Input Amp: 2.5A (@ 120V)

Mounting: Installs to a standard junction box. Total weight = 11 lbs.

The standard LM-EN12-300M configuration matches the height

of the 5 3/4" standoffs (LM-X5).

Finish: Available in Dark Bronze (DB), Chrome (CH), and Brushed

Nickel (BN).

Listing: UL & CUL Listed.

Specification Features

- Dims with magnetic low voltage dimmers.
- Output circuit breaker located on the upper lip of the canopy enclosure is a magnetic push to reset type.
- Contains integral de-buzzing coil.
- The surface mount canopy transformer is an ideal choice when the installation is on an existing ceiling.
- 5 year WAC Lighting product warranty.

WAC Lighting reserves the right to modify the design of our products as part of the company's continuous improvement program. Dec 2009