



Catalog Information

Model	Description	Input	Output (12V)	Output (24V)	Wiring	Finish
SRT-600M-12/24V	Magnetic Transformer 12/24V	120V	(2) 300W	(1) 600W	Screw Terminals	Black

Product Features

1. **Dual voltage:** Two 300-watt circuits at 12 volts, or one 600-watt circuit at 24 volts.
2. **Dimming:** Use with either magnetic or standard incandescent dimmers. Dimmers are installed on primary wiring side.
3. **Protection:** Auto reset thermal breaker on primary side. Two output circuit breakers are magnetic push to reset type.
4. **Wiring:** Integral wire terminal block, with trade sized knockouts on the side.
5. **Input current:** 5.1A
6. **Efficiency:** 96%
7. **Weight:** 13.4 lbs

Options/Accessories

Boost tap wire option to counter act voltage drop, increases voltage by ten percent.

Material

Steel enclosures

Listings

UL Listed.

W.A.C. reserves the right to change details that do not affect overall function and performance.

