

CATALOG NUMBER	TYPE
PROJECT	

MONORAIL KIT – FOUR PENDANT

MODEL LM-K592



Ordering Matrix		
Model	Series	Finish
[]	[]	[]
LM	K592	AB/BZ

Ordering Example (*model – series – finish*): LM-K592-AB/BZ

Product Details	
Description:	Monorail kit consisting of rail, components and pendants necessary to produce a 10.5' section of monorail.
Materials:	<p>The kit consists of a total of twenty four parts. The contents are</p> <ul style="list-style-type: none"> (1) LM-EN12-250E <i>surface mount transformer to power system</i> (3) LM-T3 <i>3.5' section of monorail</i> (2) LM-I <i>i-connector</i> (4) LM-X4 <i>standoff support</i> (2) LM-EC <i>rail end cap</i> (4) QP-501X42 <i>pendant socket set, 36" long</i> (4) G592 <i>glass shade, amber glass with black powder frits</i> (4) JC-50 <i>12 volt clear halogen lamp, 50 watts</i>
Finish:	The rail, pendant socket sets, and all rail components are provided in a powder coated bronze paint finish. The glass shades are provided as amber glass with black frits.
Listing:	UL & CUL Listed. 2 year W.A.C. Lighting product warranty.

Specification Features
<ul style="list-style-type: none"> • The kit comes complete with lamps, 36" low voltage pendant cord with adapter for rail, and glass shades. The pendant cord may be field shortened to any length. • The 12 volt electronic low voltage transformer provided with the LM-K592 contains auto reset, soft start, and short circuit protection features to extend lamp life and system performance.